## STR-DN1080

# 7.2 ch. Dolby Atmos® Wi-Fi® Network AV Receiver

Experience true home theater without limitations with this 7.2 channel receiver with Dolby Atmos® 3D and DTS:X object-based surround sound, plus 4K HDR and HDCP 2.2 compatibility.¹ Enjoy the flexibility of 6-in/2-out HDMl² and multi-room listening, plus voice control powered by Google Home.⁴ All in a smaller chassis that fits more places.



### **Bullets**

- Supports Dolby Atmos® 3D and DTS:X® objectbased surround sound up to 7.1ch
- 7.2 Ch. A/V Receiver (165 W x 7 @ 6 ohms, 1 kHz, THD 0.9%), plus powered 2nd zone and available 3<sup>rd</sup> zone connectivity and control
- 4K HDR compatibility with HDCP 2.2 support<sup>1</sup>
- 6-in/2-out HDMI<sup>®2</sup> flexibility
- Expand your listening and control with multi-room and Google Home compatibility<sup>4</sup>
- Digital Cinema Auto Calibration EX with speaker relocation technology
- Expand 5-channel surround sound with phantom rear surround speaker channels
- Experience amazing sound with Hi-Res Audio up to DSD 5.6
- Enhanced setup and usability via rich GUI and streamlined remote
- Dual-band Wi-Fi® for Airplay®, DLNA®, Chromecast built-in and Spotify Connect³

#### **Features**

# Experience Dolby Atmos® and DTS:X® object-based surround sound

With Dolby Atmos® and DTS:X object-based surround sound, you'll feel like you're inside the action as the sounds of people, music and objects move all around you in three-dimensional space.

### Powerhouse sound performance

With 7.2 channels of room-filling sound and 165W (165 W x 7 @ 6 ohms, 1 kHz, THD 0.9%) per channel, this powerhouse envelops you in a new level of sound performance. You can also expand your audio/video experience beyond the living room with powered 2<sup>nd</sup> zone, plus an available 3<sup>rd</sup> zone connectivity and control.

### 4K HDR compatibility with HDCP 2.21

Supporting 4K 60p 4:4:4, this receiver is a great partner for latest TVs that can display the latest content mastered in HDR (High Dynamic Range) for truly spectacular contrast and tonal range. It's also compatible with HDCP 2.2 copy protection, so you're ready for the latest 4K formats.<sup>1</sup>

#### 6-in/2-out HDMI

With six HDMI inputs and two HDMI outputs—including one dedicated second zone HDMI output—there's space for your current equipment and scope to expand.<sup>2</sup>

### Google Home compatibility and wireless multi-room listening

Connect with your Google Home control network<sup>4</sup> and enjoy voice activation as a part of a whole-home solution. Control what music you want—and where—by the sound of your voice. Even turn up the volume, skip to the next track, or stop the music, all without lifting a finger. With powerful multi-room capability, you can easily expand and control your music across multiple, compatible speakers in separate rooms. You can also cast music, podcasts and radio from 100+ apps with Chromecast built-in.

### Digital Cinema Auto Calibration EX with speaker relocation technology

Enjoy a home theater system that adjusts to your space, instead of the other way around. D.C.A.C. EX with stereo mic is Sony's unique auto calibration technology that adjusts speaker output to closely simulate the sound of optimally positioned and angled speakers. The results are nothing short of breathtaking, with the entire sound field seamlessly integrated for outstanding surround sound.

### Phantom surround speaker channels

Can't fit seven-channel surround sound? No problem. Phantom rear surround channels will transform your five-channel system into a seven-channel system.

### Experience amazing sound with Hi-Res Audio and native DSD up to 5.6

Experience digital music at its best with High-Resolution Audio. Enjoy studio-quality sound in higher-than-CD quality that feels like the artist is performing right in front of you. The receiver supports a wide variety of High-Resolution audio formats including high bit rate 192k/24-bit WAV/FLAC audio playback, and even native DSD up to 5.6MHz. Additional file formats supported include: MP3, AAC, WMA, WAV192k, FLAC 192k, ALAC, AIFF.

### Enhanced setup and usability via rich GUI and streamlined remote

Easily set-up and control the A/V receiver via an intuitive on-screen graphical user interface. Change inputs, adjust settings and confirm volume levels on-screen.

## Dual-band Wi-Fi® for Airplay®, DLNA® and Chromecast built-in and Spotify Connect3

Wirelessly connect with dual-band Wi-Fi and stream music stored on your home network or favorite devices, including Airplay compatibility with iPhone®/iPod® Touch, iPad® or iTunes®.³ You can also play Spotify using the Spotify app as a remote.³ Even jump right back into the last track you were listening to on your Spotify account by pushing the Music Service button.

## Stream audio via Bluetooth and control your experience with your phone or tablet<sup>3,5</sup>

Download the free SongPal™ and Network Audio Remote apps from iTunes ® or the Google™ Play Store and use your iPhone ® or Android™ devices with the SongPal™ app to control receiver functionality including volume and input selection.<sup>3,5</sup>

### **Specifications**

Amplifier/Receiver		
	A/V SYNC	Yes (Variable)
	A/V Sync Time/Sampling Frequency	0-300msec
	Center Speaker Lift Up	Yes
	Cross Over Frequency	17 points(40-200Hz)
	Decodable channel number	7ch + Phantom 2ch
	Digital Legato Linear	Yes
Audio Features	DSD Native Playback	Yes
Audio Features	DSEE HX	Yes (USB/Home Network/Bluetooth-RX/Spotify Connect)
	In-Ceiling Speaker Mode	Yes
	OP processing	Yes
	Pure Direct	Yes
	Sound Optimizer	Yes
	Speaker Selector	A/B/A+B/OFF
	Speaker Terminal Type	Screw (Ni)
	Analog Audio In	4
Audio Input	Coax.	1
	Optical In	1
Audio Output	Headphone Out	Yes (Gold)
	Pre Out (Subwoofer)	2
DCAC Features	Automatic Phase Matching	Yes
	D.C.A.C. EX / Advanced D.C.A.C. / D.C.A.C.	D.C.A.C. EX
	Mic	Calibration Mic: Stereo
	Phantom Surround Back	Yes
	Speaker Relocation	Yes

Input/Output Others	Bluetooth Receiver	Yes
	Bluetooth Transmitter	Yes
	Ethernet	Ethernet Port (Power over Ethernet): 1 (-)
	NFC	Yes
	USB Front(ver) / Rear(ver)	Yes (2.0) / -
	Wi-Fi	Yes (2.4GHz/5GHz), (11a/b/g/n)
	Center	165W (60hms, 1kHz, 1ch driven THD 0.9%) / 120W + 120W (60hms, 1kHz, 2ch driven THD 0.9%) / 100W + 100W (60hms, 20-20kHz, 2ch driven 0.09%)
	Front	165W (6ohms, 1kHz, 1ch driven THD 0.9%) / 120W + 120W (6ohms, 1kHz, 2ch driven THD 0.9%) / 100W + 100W (6ohms, 20-20kHz, 2ch driven 0.09%)
Output Power	Number of amp. channels	7ch
Odipui Powei	Speaker Impedance	6-16 ohms
	Surround	165W (6ohms, 1kHz, 1ch driven THD 0.9%) / 120W + 120W (6ohms, 1kHz, 2ch driven THD 0.9%) / 100W + 100W (6ohms, 20-20kHz, 2ch driven 0.09%)
	Surround Back	165W (60hms, 1kHz, 1ch driven THD 0.9%) / 120W + 120W (60hms, 1kHz, 2ch driven THD 0.9%) / 100W + 100W (60hms, 20-20kHz, 2ch driven 0.09%)
	2ch	Yes
	Audio Enhancer	Yes
	Auto Format Decoding	Yes
	Direct	Yes
Sound Field	Dolby Surround	Yes
	Front Surround	Yes
	Headphone 2ch	Yes
	Multi Stereo	Yes (Multi Ch Stereo)
	Neural:X	Yes
	Bi-AMP	Yes (Common with Surround Back)
	Center	Yes
	Front A	Yes
Speaker Out	Front B	Yes (Common with Surround Back)
speaker Oui	Height	Yes (Common with Surround Back)
	Surround	Yes
	Surround Back	Yes
	Zone2	Yes
	Center (Bass/Treble)	Yes
	Front (Bass/Treble)	Yes
Tone Control	Height (Bass / Treble)	Yes
	Surround (Bass/Treble)	Yes
	Surround Back (Bass/Treble)	Yes
	Auto Tuning	Yes
	Direct Tuning	Yes
Tuner	FM/AM	Yes (FM)
	Preset Channel (FM/AM)	TTL30 (30/-)
	Station Name	Yes
Video Input	Composite (Front)	2 (-)
video iripui	HDMI Input supporting HDCP2.2(Front)	6(0)
Video Output	Composite Monitor Out	1
VIGOO Ouipui	HDMI Output supporting HDCP2.2	2 (1:Assignable)
HDMI		

Audio Features	Audio Return Channel	Yes
	S-Select	Yes
	Dolby Atmos	Yes
	Dolby Digital	Yes
	Dolby Dual Mono	Yes
	Dolby TruHD/Dolby Digital Plus	Yes / Yes
Dagading Formata	DSD	Yes (Up to 2.8MHz 5.1ch)
Decoding Formats	DTS:X	Yes
	DTS / DTS-ES (Matrix6.1 / Discrete6.1)	Yes / Yes
	DTS 96/24	Yes
	DTS HD MA / DTS HD HR	Yes / Yes
	LPCM	Yes (Up to 192kHz/24 bit 7.1ch)
	Audio Widget	Yes
Others	BRAVIA® SYNC™ (CEC Control)	Yes (One-Touch Play, System Audio Control, System Power Off)
	Standby Through	Yes
	3D over HDMI	Yes
	4K 60p 4:4:4 Support	Yes (except VIDEO1 input)
Video Features	4K Up Scaling (From HDMI Input to HDMI Output)	Yes
	HDR	Yes
Installation		
Control Features	CIS IP Control	Yes
Cormorrealdies	IR Repeat (In/Out)	Yes(1/1)
Controller Connectivity	SDDP(Control4)	Yes
	2nd A	Speaker (Variable) / Line (Variable, Fixed)
	HDMI Zone	Yes
Features	Multi Zone Line Out Level Control (Zone2/Zone3)	Yes (Yes/-)
	Multi Zone Volume Control (Zone2/ Zone3)	Yes (Yes/-)
Language		
	English(US) or English(GB)	Yes
Help Guide	French or French(CA)	Yes
	Spanish or Spanish(LA)	Yes
Instruction Manual	English(US) or English(GB)	Yes
	French or French(CA)	Yes
	Spanish or Spanish(LA)	Yes
		Yes
	English(US) or English(GB)	
Quick Setup Guide	English(US) or English(GB)  French or French(CA)	Yes
Quick Setup Guide		
Quick Setup Guide  Network Features	French or French(CA)	Yes

DSD	
ALAC   Yes (Up to 192k	
DSD Yes (Up to 5.6M DSF Yes (Up to 5.6M PLAC Yes (Up to 5.6M PLAC Yes (Up to 5.6M PLAC Yes (Up to 192k PLAC) Yes (MADIlle Application SongPal / Vide MP3 Yes (MP3).mp3, (AV mra. (LPCM)). Yes (MP3).mp3, (AV mra. (LPCM)). Yes (Remote or Network Player/Renderer Yes/Yes (Phone/iPad Connect Yes (Nemote or Network Player/Renderer Yes/Yes (Phone/iPad Connect Yes (Nemote or Yes Wireless Multi Room Yes Wireless Multi Room Yes (Nemote or Yes Wireless Multi Room Yes (Nemote or Yes (Nemote	
DSF	(Hz/24 bit 5.1ch)
FLAC   Yes (Up to 192k	ИНz 5.1ch)
Google Cast	ИHz 5.1ch)
LPCM	kHz/24 bit 5.1ch)
Network Features    Mobile Application   SongPal / Vide	
Network Features  MP3  Music Decoding Formats for Network Client  Music Service Button Network Player/Renderer  Network Player/Renderer  Network Player/Renderer  Network Player/Renderer  Yes/Yes  SongPal compatible models with iPod/iPhone/iPad  SongPal Link Yes  Spotify Connect Wireless Multi Room Yes  Wireless Multi Room Yes  WMA Yes  Other  Easy Setup Wizard  GUI Anguage English, French, Customize Features  Customize Features  Gund Auto Standby Pes  Power Consumption  Power Consumption(Power Stand By) Power Requirement Power Requirement Power Requirement System Update (Internet/USB/PC) Yes (Yes / Yes /	'es (Up to 192kHz/24 bit 7.1ch), es (Up to 192kHz/24 bit 5.1ch)
Music Decoding Formats for Network Client  Music Service Button Network Player/Renderer  Network Player/Renderer  Network Player/Renderer  SongPal compatible models with iPod/iPhone 7 Plus, iPhone 6, it touch (5th and 5ongPal Link Yes Spotify Connect Yes Wireless Multi Room Yes Wind Yes  Other  Easy Setup Wizard Yes GUI Anguage English, French, Customize Features  Customize Features  Gui Language English, French, Coax) Sieep Timer Yes (up to 2 ho Auto Standby Yes Detachable AC Nickel Power Consumption (Power Stand By) Power Requirement Power Requirement Remote Commander System Update (Internet/USB/PC) Yes (Yes / Yes	eo & TV sideview
Music Decoding Formats for Network Client  Music Service Button  Network Player/Renderer  Network Player/Renderer  Network Player/Renderer  SongPal compatible models with iPod/iPhone 7 Plus, iPhone 6, it touch (5th and 5th	
Network Player/Renderer    SongPal compatible models with iPod/iPhone 7 Plus, iPhone 6, iPhone/iPad	AC/HE-AAC).m4a, .aac, (WMA9 Standard). wav, (FLAC).flac, .fla, (DSF).dsf, (DSDIFF).dff, (ALAC).m4a,
SongPal compatible models with iPod/ iPhone 7 Plus, iPhone 6, iPhone/iPad  SongPal Link  SongPal Link  Yes  Spotify Connect  Wireless Multi Room  Yes  WMA  Yes  Other  Easy Setup Wizard  GUI  GUI Language  Custom Preset (Easy Automation)  Yes  Customize Features  Plus (Input Assign (HDMI/Component/Opt/Coax)  Sleep Timer  Auto Standby  Pes  Detachable AC  Power Consumption  Power Consumption  Power Requirement  Power Requirement  Remote Commander  System Update (Internet/USB/PC)  Input Assign (HDMI/USB/PC)  Pes (Yes (Yes / Yes /	ontroller)
SongPal Compatible Models With IPOd/ iPhone/iPad  SongPal Link  Yes  Spotify Connect  Wireless Multi Room  WMA  Yes  Other  Easy Setup Wizard  Gul Yes (Only through Guilden)  Gul Language  Custom Preset (Easy Automation)  Customize Features  Plus, iPhone 6, intouch (5th and touch (5th and t	
Spotify Connect Wireless Multi Room Yes WMA Yes  Other  Easy Setup Wizard Yes  GUI GUI Language English, French, Customize Features  Custom Preset (Easy Automation) Foax Sleep Timer Auto Standby Power Consumption Yes  Power Consumption Power Stand By) Power Requirement Remote Commander System Update (Internet/USB/PC) Pess  Yes  Yes  0.4W Bluetooth Standbe Power Commander Simple Remote System Update (Internet/USB/PC) Yes (Yes / Yes / Y	Phone 7, iPhone 6s Plus, iPhone 6s, iPhone 6 iPhone 5s, iPhone 5c, iPhone 5, iPhone 4s, iPod d 6th generation)
Wireless Multi Room WMA Yes  Other  Easy Setup Wizard Yes  GUI Additional Features  GUI Language English, French, Custom Preset (Easy Automation) Yes  CustomPreset (Easy Automation) Yes  Input Assign (HDMI/Component/Opt/ Coax) Sleep Timer Yes (up to 2 hord Auto Standby Pewer Consumption  Power Consumption Power Stand By) Power Requirement Power Requirement Power Requirement Power Commander System Update (Internet/USB/PC) Yes  Yes  Yes  O.4W Bluetooth Standby Power Requirement Simple Remote System Update (Internet/USB/PC) Yes (Yes / Yes / Ye	
Other  Easy Setup Wizard Yes  Additional Features  GUI Yes (Only through English, French, Customize Features)  Custom Preset (Easy Automation)  Customize Features  Input Assign (HDMI/Component/Opt/Coax)  Sleep Timer  Auto Standby  Detachable AC Power Consumption  Power Consumption  Power Consumption(Power Stand By)  Power Requirement Power Requirement Power Requirement Power Remote Commander System Update (Internet/USB/PC)  Yes  Yes  O.4W Bluetooth Standard Simple Remote System Update (Internet/USB/PC)  Yes (Yes / Yes /	
Additional Features  Easy Setup Wizard  Yes  GUI  GUI Language English, French, Custom Preset (Easy Automation) Yes  Customize Features  Customize Features  Input Assign (HDMI/Component/Opt/ Coax) Sleep Timer Yes (up to 2 hore Auto Standby Yes  Detachable AC Power Consumption  Power Consumption  Power Consumption(Power Stand By) Power Requirement Power Requirement Power Requirement Simple Remote System Update (Internet/USB/PC) Yes (Yes / Yes /	
Additional Features  GUI GUI GUI Custom Preset (Easy Automation) Yes  Customize Features  CustomPreset (Easy Automation) Yes  Input Assign (HDMI/Component/Opt/ Coax) Sleep Timer Yes (up to 2 hore) Auto Standby Yes  Detachable AC Power Consumption Power Consumption Power Stand By) Power Consumption(Power Stand By) Remote Commander System Update (Internet/USB/PC) Yes (Yes / Yes	
Additional Features  GUI Language English, French, Customize Features  Custom Preset (Easy Automation) Yes  Input Assign (HDMI/Component/Opt/ Coax)  Sleep Timer Yes (up to 2 horder)  Auto Standby Yes  Detachable AC Nickel Power Consumption 240W  Power Consumption(Power Stand By)  Power Requirement 120V 60Hz  Remote Commander Simple Remote System Update (Internet/USB/PC)  Yes (Only through through the complete in the complete i	
GUI Language English, French, Custom Preset (Easy Automation) Yes  Input Assign (HDMI/Component/Opt/ Coax) Sleep Timer Yes (up to 2 hor Auto Standby Yes  Detachable AC Nickel Power Consumption 240W  Power Consumption(Power Stand By) Power Requirement 120V 60Hz Remote Commander Simple Remote System Update (Internet/USB/PC) Yes (Yes / Yes /	
Custom Preset (Easy Automation) Yes  Input Assign (HDMI/Component/Opt/ Coax) Sleep Timer Yes (up to 2 hore Auto Standby Power Consumption  General  Power Consumption(Power Stand By) Power Requirement Power Requirement Remote Commander System Update (Internet/USB/PC) Yes  1-7-1 Yes/ Yes Ves Ves Ves Ves Ves Ves Ves Ves Ves V	ugh HDMI), GUI Blending
Customize Features    Input Assign (HDMI/Component/Opt/Coax)	, Spanish
Coax   Sleep Timer   Yes (up to 2 hotel)	
Auto Standby   Yes	
Detachable AC   Nickel	ours)
Power Consumption 240W  Power Consumption(Power Stand By) 0.4W Bluetooth Stand Power Requirement 120V 60Hz  Remote Commander Simple Remote System Update (Internet/USB/PC) Yes (Yes / Yes /	
General         Power Consumption(Power Stand By)         0.4W Bluetooth Stand By Bluetooth By Bluetoo	
General         Power Consumption(Power Stand By)         Bluetooth Stand           Power Requirement         120V 60Hz           Remote Commander         Simple Remote           System Update (Internet/USB/PC)         Yes (Yes / Yes /	
Remote Commander Simple Remote System Update (Internet/USB/PC) Yes (Yes / Yes /	dby: 2.5W
System Update (Internet/USB/PC) Yes (Yes / Yes /	
	No)
USB Type A	

	AAC	Yes
	ALAC	Yes (Up to 192kHz/24 bit 5.1ch)
	DSD	Yes (Up to 5.6MHz 5.1ch)
	DSF	Yes (Up to 5.6MHz 5.1ch)
	FLAC	Yes (Up to 192kHz/24 bit 5.1ch)
LICD Marco Character	Interface	2.0
USB Mass Storage	LPCM	WAV (LPCM): Yes (Up to 192kHz/24 bit 7.1ch), AIFF(LPCM): Yes (Up to 192kHz/24 bit 5.1ch)
	MP3	Yes
	Music Decoding Formats	(MP3).mp3, (AAC/HE-AAC).m4a, .aac, (WMA9 Standard). wma, (LPCM).wav, (FLAC).flac, .fla, (DSF).dsf, (DSDIFF).dff, (AIFF).aiff, .aif, (ALAC).m4a,
	WMA	Yes
Walkman Connectivity	Music/Video/Photo	Yes/-/-
Accessories		
Accessories	Supplied Accessories	Calibration microphone FM wire antenna Remote control R03 (size-AAA) batteries
Weight and Measurements		
	Carton Dimensions (WxHxD mm)	19 5/8 x 8 3/8 x 15 5/8 inches (496 x 211 x 396 mm)
Weight and Measurements	Carton Weight (kg)	24 lb 5 oz (11 kg)
weight and mediatements	Receiver Dimension (WxHxD inches)	17 x 6 1/4 x 13 1/8 inches (430 x 156 x 331 mm)
	Receiver Weight (pound)	20 lb 1 oz (9.1 kg)

- 1. Requires 4K TV, 4K video player and High speed HDMI cables with Ethernet. (Premium High Speed HDMI cables with Ethernet is required for 4K 60p 4:4:4 8 bit and 4K 60p 4:2:0 10 bit, etc.).
- 2. Requires HDMI® cable sold separately. (HDMI-24P)
- 3. SongPal app must be downloaded from the iTunes App store or Google Play store. Requires devices connected to the same wireless home network. Network services, content and software of this product may be subject to individual terms and conditions and changed, interrupted or discontinued at any time and may require fees, registration and credit card information.
- 4. Google product model XXX (sold separately) compatible with [select] Sony sound bars {OR INSERT MODELS X, Y, and Z}. Requires compatible devices connected to the same wireless home network. Download the Google home app from the iPhone App Store or Google Play. Subject to third party app terms and conditions. User must link compatible devices in order to control operation. Once download is complete, the Google Home feature may be connected to the Sony device to access the voice control function.
- 5. Interoperability and compatibility among Bluetooth® devices vary.

©2016 Sony Electronics, Inc. All rights reserved. Reproduction in whole or in part without written permission is prohibited. Sony, SongPal and the Sony logo are trademarks and or registered trademarks of Sony Corporation. The terms HDMI High-Definition Multimedia Interface, and the HDMI Logo are trademarks or registered trademarks of HDMI Licensing, LLC in the United States and other countries. Bluetooth and the Bluetooth logo are trademarks of Bluetooth SIG, Inc. The N Mark is a registered trademark of NFC Forum, Inc. and any use of such marks by Sony Corporation is under license. Android, Google Play, Google Home, the Google Play logo, and Chromecast are trademarks of Google Inc. Spotify and Spotify logos are trademarks of the Spotify Group. All other trademarks are trademarks of their respective owners. Features and specifications are subject to change without notice.